



#2 Solid Bare Copper Conductor

DESCRIPTION

- #2 solid soft-drawn bare copper cable
- Cross-sectional area of 66,360 circular mils
- Outside diameter of .257"
- Finished weight of 201 pounds per 1000 feet
- Meets the requirements of ASTM B-3

APPLICATIONS

- Used for grounding electrical systems where high conductivity is required