



#4 Solid Bare Copper Conductor

DESCRIPTION

- #4 solid soft-drawn, bare copper cable
- Cross-sectional area of 41,470 circular mils
- Outside diameter of .204"
- Finished weight of 126 pounds per 1000 feet
- Meets the requirements of ASTM B-3

APPLICATIONS

- Used for grounding electrical systems where high conductivity is required